

## Intara CX

Article number: 51380019

## LIGHT TECHNOLOGY


LED COB
Light colour Fish-Seafood
Luminous flux 1570 lm
System power 23 W
Luminaire Efficiency 68 lm/W
Reflector Flood
Beam angle 40°

## **LUMINAIRE**

Rotation angle 350°
Swivel angle +30° / -30°
Weight 0.72 kg
Protection rating . class IP20 . III
Luminaire colour white

## OPCJA

RAL-colours, NCS-colours (powder coating or wet spraying) on inquiry, surface alloys on inquiry, honeycomb louver





Recessed directional spot with LED, rated life of the LED L80/B10 > 50000 h, chromaticity tolerance 2 SDCM (initial), reflector with circular light distribution pattern, reflector pure aluminium 99,99% in MIRO-Silver®, segmented and faceted, exchangeable reflector unit in high-sheen black plastic, with glass cover, luminaire head designed as heat sink die-cast aluminium, black anodized, rotation angle 350°, swivel angle +30°/-30°, assembly ring die-cast aluminum, front ring and trim in plastic, plastic clamp spring for ceiling attachment, white, separate driver unit

76500102 driver unit, Fix Current, IP54,

220-240 V / 50-60 Hz, 600 mA, camera-compatible, up to 2.5 KV interference resistance, SELV, max. 34 luminaires per circuit (B16A fuse)

76500106 driver unit, DALI, IP54,


220-240 V / 50-60 Hz, 600 mA, camera-compatible, up to 2.5 KV interference resistance, SELV, max. 24 luminaires per circuit (B16A fuse)


76500034 driver unit, Fix Current,

220-240 V / 50-60 Hz, 600 mA, camera-compatible, up to 2.5 KV interference resistance, SELV, max. 34 luminaires per circuit (B16A fuse)

76500039 driver unit, DALI,

220-240 V / 50-60 Hz, 600 mA, with GST18/5-pin connector, incl. 5-conductor feed-through wiring, camera-compatible, up to  $2.5~{\rm KV}$  interference resistance, SELV, max. 24 luminaires per circuit (B16A fuse)





Note: All data are typical values. System features may change with product improvements due to technical advances. Errors excepted.















www.baero.com 17.10.2025